

# RemoteAmp Two™

## Headphone Amplifier




### FEATURES

	RA	R2
» Compatible with TW (Two-Wire) Party-Line Intercoms (Listen-Only)	•	•
» XLR Line level Input	•	•
» 1/8" (3.5mm) Stereo Line Input Jack	•	•
» 1 Master Level Control	•	
» 2 Independent Level Controls		•
» Hi-Z/Lo-Z Termination of 3.5mm Input		•
» 1/4" Stereo Headphone Jack	•	•
» 1/8" (3.5mm) Stereo Headphone Jack	•	•
» Stainless Steel Belt Clip	•	•
» >20 Hours on one 9V Battery	•	•

RemoteAmp Two is shown for comparison


**RA** = RemoteAmp    **R2** = RemoteAmp Two



### Mono IFB Plus Stereo Audio Input.

RemoteAmp Two provides a listen only connection for mono IFB or full bandwidth stereo music listening. Separate volume controls for the XLR and 3.5mm line input jacks allow a simple mix of mono and stereo sources. The XLR line level input accepts either a balanced mono signal, or a party line intercom feed (listen-only). The 500 mW, 1/4" stereo headphone jack will cut through any crowd noise. Connect an IFB earpiece to the 3.5mm earpiece jack for mono operation.

### BLOCK DIAGRAM



### SPECIFICATIONS



#### Line Input

Female XLR:	4k ohms 100 mV RMS (-18 dBu nom, +12 dBu max)
1/8" (3.5mm) TRS Stereo:	20k ohms, Switchable to 50 ohms -10 dBu nom

#### Headphones

1/4" Stereo Headphone:	8 ohms, 500 mW per channel
1/8" (3.5mm) Stereo Headphone:	10 ohms, 430 mW per channel

#### Misc.

Stereo Separation:	55 dB
Frequency Response:	20 Hz - 20 kHz
Power:	One 9 volt Alkaline Battery
Size:	4.7" x 3.75" x 1.65" (12 x 9.5 x 4.2 cm)
Weight:	10 oz. (275 g)